

## Wireless Communications Channels Lecture 2: Propagation Mechanisms

EITN85: Meifang Zhu(e-mail: meifang.zhu@eit.lth.se) Department of Electrical and Information Technology, Lund University



#### **Recap: Last Lecture**



#### Contents

#### **Propagation mechanisms:**

- □ Free space attenuation
- Reflection and transmission
- Diffraction
- □ Diffuse scattering
- □ Waveguiding

#### **Examples from real world propagation scenarios**



#### Free space attenuation

 Assume TX and RX antennas in free space and would like to derive the received power as a function of link distance and transmit power
Assume omnidirectional antennas for now





#### Free space attenuation

- Assume TX and RX antennas in free space and would like to derive the received power as a function of link distance and transmit power (omnidirectional antennas)
- Energy conservation: integral of power density over any closed surface = transmit power
- □ If TX antenna radiates isotropically, then power density on surface is  $P_{\text{TX}}/(4\pi d^2)$ . Then,

$$P_{\rm RX}(d) = P_{\rm TX} \frac{1}{4\pi d^2} A_{\rm RX}$$

Power impinging on the area which is **collected** by the RX antenna!



#### Free space attenuation

□ If TX antenna does not radiates isotropically, then power density on surface is  $P_{TX}G_{TX}/(4\pi d^2)$ . Then,

$$P_{\rm RX}(d) = P_{\rm TX} G_{TX} \frac{1}{4\pi d^2} A_{\rm RX}$$

- Product of TX power and gain is known as: effective isotropic radiated power (EIRP)
- □ Relationship between effective area and antenna gain:  $G_{\text{RX}} = \left(\frac{4\pi}{\lambda^2}\right) A_{\text{RX}}$



#### Free space loss: Friis' law

Received power, with antenna gains  $G_{TX}$  and  $G_{RX}$ :



#### Question: What happens if *d* is 0 in \*?



#### Free space loss: Friis' law implications

$$P_{RX}\left(d\right) = \frac{G_{RX}G_{TX}}{L_{free}\left(d\right)}P_{TX} = P_{TX}\left(\frac{\lambda}{4\pi d}\right)^2 G_{RX}G_{TX}$$



8

## Free space loss: What and where is the far field?

The free space loss calculations are only valid in the "far field" of the antennas.

Far-field conditions are assumed far beyond the "Rayleigh" distance:

$$d_{R} = \frac{2L_{a}^{2}}{\lambda}$$

where  $L_a$  is the largest dimension of the antenna.



#### Another rule of thumb is: "At least 10 wavelengths"

#### Quiz

## Compute the Rayleigh distance of a square patch antenna receiving a signal with a gain of 10 dB.



#### The d<sup>-4</sup> law – l

Instead of just considering a direct path, let's look at the following scenario





11

## Continuation of Slide (10): How?



12

## The d<sup>-4</sup> law – II



• However .....

- n=4 is not a universal decay exponent
- Theoretical model is not fulfilled in practice
- Breakpoint is rarely where theoretically predicted
- Second breakpoint at the radio horizon



## Fundamental propagation mechanisms



**Wireless Communication Channels** 

UNIVERSITY

#### **Complex dielectric constant**

Lets take a homogeneous planewave incident onto a dielectric half-space



dielectric constant, permittivity

#### Describes the dielectric material in one single parameter

Examples	Permittivity	conductivity
Concrete	6	10 <sup>-2</sup>
Gypsum	6.5	10 <sup>-2</sup>
Wood	23	<b>10</b> <sup>-11</sup>
Glass	5	10 <sup>-12</sup>
Air	1	



#### **Reflection and transmission**



**Reflected angle:** 

$$\Theta_{e} = \Theta_{r}$$

Transmitted angle:

$$\frac{\sin\Theta_{t}}{\sin\Theta_{e}} = \frac{\sqrt{\varepsilon_{1}}}{\sqrt{\varepsilon_{2}}}$$



16

# What is Reflection and Transmission Dependent on?



17

#### TM and TE Component Behaviors



#### Transmission through layered structures



Wall with thickness d and two dielectrics



19

## Diffraction: The principle



- Single or multiple edges
- makes it possible to go behind corners
- less pronounced when the wavelength is small compared to objects



20

#### Diffraction: Huygen's principle



Each point of a wavefront can be considered as a source of a spherical wave

Bending around corners and edges



## **Diffraction coefficient**



#### The Fresnel integral is defined

$$F(v_{\rm F}) = \int_{0}^{v_{\rm F}} \exp\left(-j\pi \frac{t^2}{2}\right) dt.$$

#### **Total field**

$$E_{\text{total}} = \exp(-jk_0 x) \left( \frac{1}{2} - \frac{\exp(-j\pi/4)}{\sqrt{2}} F(v_F) \right)$$
  
Fresnel integral

with the Fresnel parameter

$$v_{\rm F} = \alpha_k \sqrt{\frac{2d_1d_2}{\lambda(d_1+d_2)}}$$

